

Special Multi-Channel Receivers (4013)



PRK 040, PRK 040I, PRK 040D
Special Multi-Channel Receivers

Special multi-channel receivers rated for reception of radio signal.

Models:

- PRK 040 – open radio channel;
- PRK 040I – open radio channel + Spectrum Inversion decoder;
- PRK 040D – open radio channel + Delta Modulation decoder.

Features:

- Individual programming of each channel (frequency synthesizer);
- Automatic Carrier Operated Recording;
- Battery Low indicator.
- Low power consumption;
- External power supply (with ON indication) 6 - 9 V.
- Tough milled case.

The receivers are designed in a milled metal case. Each receiver is equipped with minimized quantity of controls - volume control combined with power ON/OFF switch, Channel selector, Carrier LED indicator, earphones output, SMA antenna output and the Recorder output combined with Recorder Remote Control function.

Goldman Trades Surveillance and Security Equipments
57 Charing Cross Road
London
WC2H 0NE
United Kingdom

Registration No: 05871589
VAT: 911405858
Tel: +44-2072873621
Fax: +44-2072873621
admin@goldmantrades.com
<http://www.goldmantrades.com>

**SPECIFICATIONS:**

Receiving frequency bandwidth	416 - 421 MHz
Quantity of memory channels	10
Modulation	WFM
Sensitivity (at signal/noise 10 dB):	
- PRK 040	No less 0.5 μ V
- PRK 040I	No less 1 μ V
- PRK 040D	No less 1.5 μ V
Current consumption at an average volume	No more 50 mA
External power supply	6 - 9 V
Internal power supply	3 AAA x 1.5 V
Dimensions	130 x 67 x 20 mm

Goldman Trades Surveillance and Security Equipments
57 Charing Cross Road
London
WC2H 0NE
United Kingdom

Registration No: 05871589
VAT: 911405858
Tel: +44-2072873621
Fax: +44-2072873621
admin@goldmantrades.com
<http://www.goldmantrades.com>